












전구 사양

아래의 표는 큐라이트에서 사용하고 있는 각종 전구를 제품별로 분류한 전구 일람표입니다. 전구 교체 시 해당 제품의 전구 사양을 정확히 확인하여 규격에 맞는 전구를 사용하기 바랍니다. 규격에 맞지 않는 전구 사용은 고장의 원인이 됩니다.

외형	일련번호	사양	규격	사용 전압	소비 전류	적용 제품
	1	14V / 5W	G14 9S	12V	0.357A	S50, ST45
	2	27V / 5W	G14 9S	24V	0.185A	
	3	120V / 5W	T16 x 28 9S	110V	0.042A	S50, ST45
	4	240V / 5W	T16 x 28 9S	220V	0.021A	
	5	12V / 5W	T16 x 35 15S	12V	0.417A	S60, S80, SR SJ, SJD
	6	24V / 5W	T16 x 35 15S	24V	0.208A	
	7	120V / 5W	T16 x 35 15D	110V	0.042A	S60
	8	240V / 5W	T16 x 35 15D	220V	0.021A	
	9	12V / 10W	T16 x 35 15S	12V	0.833A	S100, S125 SE ST56, ST80
	10	24V / 10W	T16 x 35 15S	24V	0.417A	
	11	48V / 10W	T16 x 35 15S	48V	0.208A	
	12	120V / 10W	T16 x 35 15S	110V	0.083A	S100, S125 ST56, ST80
	13	240V / 10W	T16 x 35 15S	220V	0.042A	
	14	48V / 10W	T16 x 35 15D	48V	0.208A	
	15	120V / 10W	T16 x 35 15D	110V	0.083A	
	16	240V / 10W	T16 x 35 15D	220V	0.042A	
	17	12V / 15W	G23 15S	12V	1.250A	SK, S150, SH1, SH2, SED SD, SHD, SHD2 SMD, SESA, SEBA, SEA
	18	24V / 15W	G23 15S	24V	0.625A	
	19	48V / 15W	G23 15S	48V	0.313A	
	20	120V / 15W	G23 15S	110V	0.125A	
	21	240V / 15W	G23 15S	220V	0.063A	
	22	120V / 15W	G23 15D	110V	0.125A	S150, SH1, SH2, SED SD, SHD, SHD2 SMD, SESA, SEBA, SEA
	23	240V / 15W	G23 15D	220V	0.063A	
	24	12V / 23W	S25 15S	12V	1.916A	S150, SH2, SD, SMD SESA, SEBA, SEA
	25	24V / 23W	S25 15S	24V	0.958A	
	26	48V / 25W	T23 x 62 15D	48V	0.521A	S150, SH2, SD, SMD SESA, SEBA, SEA
	27	120V / 25W	T23 x 62 15D	110V	0.208A	
	28	240V / 25W	T23 x 62 15D	220V	0.104A	
	29	12V / 35W	RP35 15S	12V	2.917A	S180
	30	24V / 35W	RP35 15S	24V	1.458A	

외형	일련번호	사양	규격	사용 전압	소비 전류	적용 제품
	31	120V / 35W	RP35 15D	110V	0.292A	S180
	32	240V / 35W	RP35 15D	220V	0.146A	
	33	110V / 60W	E26 ES	110V	0.545A	S150, SH2, SD, SMD SESA, SE, SEBA, SEA
	34	220V / 60W	E26 ES	220V	0.272A	
	35	12V / 30W	A60 E26	12V	2.500A	S150, SH2 SD, SMD
	36	24V / 60W	A60 E26	220V	2.500A	
	37	110V / 60W	A60 E26	110V	0.545A	S150, SH2 SD, SMD
	38	220V / 60W	A60 E26	220V	0.272A	
	39	12V / 35W	15S 할로겐	12V	2.917A	SKH
	40	24V / 35W	15S 할로겐	24V	1.458A	
	41	110V / 35W	15D 할로겐	110V	0.318A	S150, SH2, SD, SMD SESA, SE, SEBA, SEA
	42	220V / 35W	15D 할로겐	220V	0.159A	
	43	12V / 55W	15S 할로겐	12V	4.583A	S150, SH2, SD, SMD SESA, SE, SEBA, SEA
	44	24V / 55W	15S 할로겐	24V	2.292A	
	45	120V / 55W	15D 할로겐	110V	0.458A	S150, SH2, SD, SMD SESA, SE, SEBA, SEA
	46	240V / 55W	15D 할로겐	220V	0.229A	
	47	220V~350V	BGA2120 -BBC I형 크세논램프		4W	S80S, S80AS SNE-S, SNES-S, SE-S
	48	200V~550V	EUB0641 -1A(G) U형 크세논램프		6W	S100S, S125S S150US, S150RS SJS, SJSP SH1S, SH2S SEDS, SDS, SMDS SHDS, SHD2S SCDWS, SCDFS SESAS, SEBAS, SEAS
	49	280V~400V	BH0647(G) W형 크세논램프		16W	S180US, S180UHS